



OptiCoin 14 and OptiCoin 14 touch

Coin deposit system

The OptiCoin 14 offers professional coin deposit service for every self-service area. Due to its special self-cleaning mechanism it is very resistant against foreign elements and dirt. Easy handling and its unique modularity in terms of different coin-bin solutions make the OptiCoin 14 adaptable for a broad field of applications. The standard version comes with a 4-line dialogue display, but it can be upgraded with a PC/touch TFT combination. Innovative materials in industrial quality for coin-disk and coin-path ensure high counting speed but a low noise level.



Verified
Sensor



Mix
Counter



Self
Service



Staff
Operated

Flexible use

- Different coin-bin solutions with CIT-box or multiple-coin bag solutions for reusable bags or one-way bags (safe bags)
- Pre-cleaning due to intelligent dirt-separators
- Blockage-checker separates and rejects foreign objects automatically
- Configurable access-control (optional)

Easy and clear operation

- Operation due illuminated, alphanumeric 4-line dialogue display or touch-TFT possible (optional)
- Preselection of maximum capacity and commission model even in supervisor-mode configurable
- Electronic journal for download of statistical data and technical information
- Possible auto-accounting when removing coin-bin
- Graphic-capable thermal printer with Barcode print

Modular coin-detection system in its 4th generation

- Magnetic sensor for coin alloy
- Capacitive sensor of coin-mass
- Matrix-sensor of coin-profile
- CCD diameter sensor with 256px resolution (optional)



Dialogue display and
swipe card reader



Low noise coin disk with
cleaning-holes



Coin-tray



Receipts



Different coin-bin
solutions available



Blockage-checker

PRODUCT INFORMATION

Counting speed	Up to 1.200 coins/minute	Capacity coin hopper	1.200 coins
W x D x H	485 x 580 x 1.234 mm	Weight	115 kg
Power supply	100-240 V, 50-60 Hz	Colour	RAL 7035/7021

OPTIONS

Configurable access control for 24h use	Blockage-checker
Multi-coin-bin solution with preselection for 2, 4 or 6 coin-bins	Diameter sensor (CCD)
Touch TFT and PC/Windows professional	Motorized card reader
	Air flow sensor cleaner